

## AD1000 Telephone Voice Dialler

Features: 20 Second Single Voice Message, 8 Engineer Programmable Telephone Numbers, 1 User Follow Me Telephone Number, Tone, Pulse & PABX Dialling, Audible Alert After Dialling, Alarm Trigger OV or 12Vdc, Recall Programmed Telephone Numbers, Non Volatile Memory, Lightning Protection On Telephone Line Input.



### Product Specification

#### General Specifications

<b>Voice Message</b>	Single 20 second message
<b>Telephone Numbers</b>	7 Installer programmed, 1
<b>Dialling</b>	Tone or pulse dialling, Slow dialling PABX system dialling Audible alert after dialling, Telephone numbers dialled twice

#### Installer Programmable Functions

Change installer code
Installer code burn in
Pulse dialling
Tone dialling
Operation through PABX system
Slow telephone number dialling
Audible alert after alarm dialling
Entering installer programmed telephone numbers
Deleting programmed telephone numbers
Recording voice message

#### Order Number

LY69-049-83

#### User Programmable Functions

Change user code
Change follow me telephone number
Delete follow me telephone number
Display follow me telephone number

#### Electrical Specification

<b>Low voltage input</b>	11-14Vdc
<b>Current drain standby</b>	20mA
<b>Current drain alarm</b>	85mA
<b>Alarm Trigger</b>	OV or 12Vdc

#### Technical Specification

<b>Plastic housing material</b>	ABS
<b>Dimensions</b>	134mm X Height 105mm X Width 30mm
<b>Weight</b>	200g

#### European Standards

Conforms to European law (EU) Low Voltage Directives LVD 73/23/EEC (amended 93/68/EEC) and Electro-magnetic Compatibility (EMC) 89/336/EEC (Amended by 92/31/EEC and 93/68EEC)